



## MSA Carburetor Replacement Parts Application & Cross Reference Chart

Precision Carb P/N	Throttle Shaft	Gasket Kit	Float Kit	Float Shaft	Idle Needle	Venturi	Nozzle	Pump Plunger	Idle Tube	Float Valve	Major OH Kit	Minor OH Kit	Bowl Gasket	Pump Inlet Valve	Pump Discharge Valve
<b>Continental</b>	13-	16-	30-	32-	43-	46-	47-	194-	229-	233-	286-	778-	16-	36-	36-
<a href="#">10-3237-1</a>	1531	653	804	32	564	F11	851	593	566	615	1616	904	B75	525	540
<a href="#">10-3965-12</a>	1533	646	802	35	648	A226	749	580	584	614	2007	914	A31	587	na
<a href="#">10-4115-2</a>	1520	696	804	32	564	F12	850	593	587	615	1636	901	B75	525	540
<a href="#">10-4439-1</a>	1531	653	804	32	564	F11	851	593	566	615	1616	904	B75	525	540
<a href="#">10-4893-1</a>	1533	646	802	35	648	A226	749	580	584	614	1669	914	A31	587	na
<a href="#">10-4894-1</a>	1520	696	804	32	564	F12	850	593	587	615	1636	901	B75	525	540
<a href="#">10-4895-1</a>	1531	653	804	32	564	F11	851	593	566	615	1616	904	B75	525	540
<a href="#">10-5192</a>	1533	646	802	35	648	A226	831	580	584	614	1743	914	A31	587	na
<a href="#">10-5284</a>	1533	646	802	35	648	A226	847	580	584	614	1790	914	A31	587	na
<b>Lycoming</b>	13-	16-	30-	32-	43-	46-	47-	194-	229-	233-	286-	778-	16-	36-	36-
<a href="#">10-3678-32</a>	1521	676	804	32	564	F10	773	581	587	615	1623	924	B75	525	540
<a href="#">10-3878</a>	1522	625	802	35	648	A226	739	605	590	614	1670	912	A31	587	na
<a href="#">10-4164-1</a>	1522	625	802	35	648	A226	755	591	589	614	1661	910	A31	587	na
<a href="#">10-4404</a>	1523	625	802	35	648	A227	779	605	592	614	1643	908	A31	587	na
<a href="#">10-4404-1</a>	1523	646	802	35	648	A227	779	605	592	614	1643	909	A31	587	na
<a href="#">10-5062</a>	1521	676	804	32	564	F10	813	581	587	615	1622	924	B75	525	540
<a href="#">10-5135</a>	1521	676	804	32	564	F10	828	581	587	615	1690	924	B75	525	540
<a href="#">10-5199</a>	1519	713	804	32	564	F9	833	na	603	615	1740	905	B85	na	na
<a href="#">10-5217</a>	1521	676	804	32	564	F10	828	581	587	615	2013	924	B75	525	540
<a href="#">10-5219</a>	1526	763	800	88	A93	A257	A109 A128	625	588	614	1760	917	B56	587	596
<a href="#">10-5220</a>	1520	696	804	32	564	F9	833	593	603	615	1771	901	B75	525	540
<a href="#">10-5221</a>	1526	764	800	88	362	A257	A109	na	589	614	1769	918	B56	na	na
<a href="#">10-5267</a>	1520	696	804	32	564	F9	846	593	603	615	1783	901	B75	525	540